



3 Minutes



Before You Start:

- Make sure you have a router and high-speed Internet access (not included).
- Connect your DVR to your router using an Ethernet cable (see the Quick Connection Guide for details).
- Upgrade your DVR firmware and client software or mobile app to the latest versions.
- Please note that an upload speed of 1 Mbps is required for remote video streaming. Up to 3 devices may connect to the system at the same time.

1A iPhone

- Install the free **FLIR Cloud™** app from the App Store. Tap the **FLIR Cloud™** icon to open the app.
- Tap **Sign up** and enter your email address and password to create a new account.
- Tap **Device List** and then tap **+**.
- Configure the following:

- Tap **Scan QR Code** and line up the QR code on the top of the DVR using the camera on your iPhone.

OR under **Device ID**, manually enter the Device ID printed on the label.

EXAMPLE
- Tap **Connect**. You will be prompted to change the DVR password.
- Enter a new 6 character password and tap **OK**. This password will be used to log on to your system from now on.
- The app opens in Live View and streams video from all connected cameras.

1B iPad

- Install the free **FLIR Cloud™** app from the App Store. Tap the **FLIR Cloud™** icon to open the app.
- Tap **Device List** and then tap **+**.
- Tap **Add**.
- Configure the following:

- Tap **Start Scanning** and line up the QR code on the top of the DVR using the camera on your iPad.

OR under **Device ID**, manually enter the Device ID printed on the label.

EXAMPLE
- Tap **Start Live View**. You will be prompted to change the DVR password.
- Enter a new 6 character password and tap **OK**. This password will be used to log on to your system from now on.
- The app opens in Live View and streams video from all connected cameras.

1C Android

- Install the free **FLIR Cloud™** app from the Google Play Store. Tap the **FLIR Cloud™** icon to open the app.
- Tap **Sign up** and enter your email address and password to create a new account.
- Tap **Device List** and then tap **+**.
- Configure the following:

- Tap **Scan QR Code** and line up the QR code on the top of the DVR using the camera on your phone or tablet.

OR under **Device ID**, manually enter the Device ID printed on the label.

EXAMPLE
- Tap **Connect**. You will be prompted to change the DVR password.
- Enter a new 6 character password and tap **OK**. This password will be used to log on to your system from now on.
- The app opens in Live View and streams video from all connected cameras.



LOREX® Quick PC/MAC Guide

NOTE: PC/Mac setup is not required to connect on a smartphone or tablet. See reverse for smartphone/tablet setup.



15 Minutes

2 Find your Device ID

The **Device ID** is printed on a label on the top panel of the DVR.



Record your information below:

DEVICE ID: _____



3 Connecting on PC or Mac

a Download and install the client software.

- **PC Users:** Download and install the **Client Software for PC** from www.lorextechnology.com/support.
- **Mac Users:** Download and install the Client Software for Mac from www.lorextechnology.com/support. Double click to extract the software. Then, drag the software to **Applications**.

b Once installation is finished, double-click the **FLIR Cloud Client™ icon** () on the desktop or Applications list.

c Log into the Client Software using the Client Software user name (default: **admin**) and password (default: **admin**) and then click **Login**.



Click **Add Device**

e Enter the following information:

- 1 **Device Name:** Choose a name for your system of your choice.
- 2 **Device ID:** Manually enter the Device ID printed on the label.
- 3 **Client Port:** Enter the **Client Port** (default: **35000**).
- 4 **User Name:** Enter the **DVR's User Name** (default: **admin**).
- 5 **Password:** Enter the **DVR's Password** (default: **000000**).

EXAMPLE





Click **Add**

f You will be prompted to change the DVR password. Click **OK**.

g Enter a new 6 character password and tap **OK**. This password will be used to connect to your system from now on.

h Click  then .

i Click and drag **Default Group** to the display window to open your cameras in live view.



Congratulations! You can now connect over the Internet to view and playback video on your computer.

Troubleshooting

If you are having trouble connecting, try the following:

- Restart the DVR using the power switch
- Ensure the DVR is connected to the router using an Ethernet cable and then restart the DVR
- Double check the Username, Password, and Client Port
- Ensure your DVR has the latest firmware
- For slower Internet connections, reduce bitrate settings to CIF, 10FPS, 96 or 128kbps. See instruction manual at www.lorextechnology.com/support

Quick Reference

Default access information:

- Default user name: **admin**
- Default password: **000000**

See the label on top of your DVR for your Device ID

Default system ports:

- HTTP Port: **80**
- Client Port: **35000**

If you have forgotten your password, contact Lorex technical support

Need Help?

Visit www.lorextechnology.com/support

It's all on the Web
Software and complete instruction
manual available on:



www.lorextechnology.com/support

Information in this document is subject to change without notice. As our products are subject to continuous improvement, Lorex Corporation and our subsidiaries reserve the right to modify product design, specifications and prices, without notice and without incurring any obligation. E&OE © 2015 LOREX. All rights reserved.

INR110_SERIES_QNG_EN_R1